

HALO RGBW AURA LED 19 x 15W		
25 Channel Mode		
CH	Function	DMX Value
CH1	Strobe	0 - 2
		3 - 128
		129 - 255
CH2	Dimmer	0 - 255
CH3	Zoom	0 - 255
CH4	Pan	0 - 255
CH5	Pan Fine	0 - 255
CH6	Tilt	0 - 255
CH7	Tilt Fine	0 - 255
CH8	Reset	0 - 199
		200 - 255
CH9	LED Function	0 - 10
		11 - 20
		21 - 30
		31 - 40
		41 - 50
		51 - 60
		61 - 70
		71 - 80
		81 - 123
		124 - 167
		168 - 209
201 - 255		
CH10	Red	0 - 255
CH11	Green	0 - 255
CH12	Blue	0 - 255
CH13	White	0 - 255
CH14	Rainbow	0 - 255
CH15	LED dark time	0 - 255
CH16	LED dark to bright	0 - 255
CH17	LED bright to dark	0 - 255
CH18	LED bright time	0 - 255
CH19	Pan/Tilt speed	0 - 255
CH20	Aura Strobe	0 - 2
		3 - 128
		129 - 255
CH21	Aura Dimmer	0 - 255
CH22	Aura Red	0 - 255
CH23	Aura green	0 - 255
CH24	Aura Blue	0 - 255

Informations
No Function (Open)
Strobe slow -> fast
Random Strobe slow -> fast
0 ... 100%, dark to bright
60° ... 10°
Pan Coarse 0° ... 540°
Tilt Coarse 0° ... 270°
Normal Operation
System Reset
No Function
Red
Green
Yellow
Blue
Violet
Cyan
White 8000K
Colorchase R, G, B, W slow to fast
Colorfade R, G, B, W Slow to fast
Colorchase R, G, B, W plus pastel Slow to fast
Colorfade R, G, B, W plus pastel Slow to fast
Red Dimmer
Green Dimmer
Blue Dimmer
White Dimmer
Rainbow fade R ...G ... B ... W
Dark time
Bright to Dark time
Dark to bright time
Bright time
X - Y Movement speed fast to slow
No Function (Open)
Strobe slow -> fast
Random Strobe slow -> fast
0 ... 100%, dark to bright
Backled Red Dimmer
Backled Green Dimmer
Backled Blue Dimmer